



US007960867B2

(12) **United States Patent**
Issa et al.

(10) **Patent No.:** **US 7,960,867 B2**
(45) **Date of Patent:** **Jun. 14, 2011**

(54) **METHODS AND SYSTEMS FOR WIRELESS ENERGY AND DATA TRANSMISSION**

(75) Inventors: **Anthony Francis Issa**, Orlando, FL (US); **Jeffrey Messer**, San Bernadino, CA (US); **John Michael Tobias**, Toms River, NJ (US)

(73) Assignee: **Extremely Ingenious Engineering**, Orlando, FL (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 266 days.

(21) Appl. No.: **12/288,586**

(22) Filed: **Oct. 21, 2008**

(65) **Prior Publication Data**

US 2009/0134711 A1 May 28, 2009

Related U.S. Application Data

(60) Provisional application No. 61/004,373, filed on Nov. 27, 2007.

(51) **Int. Cl.**

H01F 27/28 (2006.01)

H01F 38/00 (2006.01)

(52) **U.S. Cl.** **307/104**

(58) **Field of Classification Search** **307/104**
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

514,168 A 2/1894 Tesla
593,138 A 11/1897 Tesla
645,576 A 3/1900 Tesla
649,621 A 5/1900 Tesla
685,953 A 11/1901 Tesla

685,954 A 11/1901 Tesla
685,955 A 11/1901 Tesla
685,956 A 11/1901 Tesla
685,957 A 11/1901 Tesla
685,958 A 11/1901 Tesla
787,412 A 4/1905 Tesla
1,119,732 A 12/1914 Tesla
2,205,204 A 6/1938 King
3,432,664 A 3/1969 Robison
3,758,869 A 9/1973 Wagner
3,781,647 A 12/1973 Glaser
3,909,736 A 9/1975 Huchital et al.
4,379,253 A 4/1983 Myer
4,485,426 A 11/1984 Kerls
4,685,047 A 8/1987 Phillips, Sr.
4,717,889 A 1/1988 Engelmann
4,727,297 A 2/1988 Wolze
4,872,100 A 10/1989 Diaz

(Continued)

OTHER PUBLICATIONS

International Preliminary Report for PCT/US2008/007655 dated Dec. 22, 2009.

(Continued)

Primary Examiner — Jared J Fureman

Assistant Examiner — Hal I Kaplan


(74) *Attorney, Agent, or Firm* — Milbank Tweed Hadley & McCloy LLP

(57)

ABSTRACT

System and methods for wireless energy and data transmission are described. One aspect includes an emitter and receiver. The emitter may include primary and secondary emitting windings. The receiver may include primary and secondary receiver windings. In further aspects, the emitter may include a tertiary emitting winding and the receiver may include a tertiary receiver winding. In one aspect, the emitter uses driving circuitry and the receiver uses rectifying circuitry and one or more capacitors. In further aspects, the emitter and receiver are reversible.

39 Claims, 16 Drawing Sheets



U.S. PATENT DOCUMENTS

4,916,379	A	4/1990	Wand et al.
4,937,832	A	6/1990	Rocca
4,945,721	A	8/1990	Cornwell et al.
4,956,579	A	9/1990	Albright
4,963,792	A	10/1990	Parker
5,103,366	A	4/1992	Battochi
5,173,643	A	12/1992	Sullivan et al.
5,225,623	A	7/1993	Krasnow
5,276,281	A	1/1994	Sato et al.
5,281,898	A	1/1994	Albright
5,739,997	A	4/1998	Gross
5,818,180	A	10/1998	Canclini
5,841,239	A	11/1998	Sullivan et al.
5,864,212	A	1/1999	Sullivan
6,052,017	A	4/2000	Pidutti et al.
6,118,229	A	9/2000	Lee
6,166,869	A	12/2000	Pidutti et al.
6,198,335	B1	3/2001	Pakriswamy
6,259,305	B1	7/2001	Pakriswamy
6,272,694	B1	8/2001	Weaver et al.
6,320,508	B1	11/2001	Giesler et al.
6,522,089	B1	2/2003	Duong et al.
6,549,044	B2	4/2003	Brambilla et al.
6,798,716	B1	9/2004	Charych
6,883,509	B2	4/2005	Porter et al.
6,906,486	B2	6/2005	Berroth et al.
6,906,495	B2	6/2005	Cheng et al.
6,911,848	B2	6/2005	Vinciarelli
6,930,893	B2	8/2005	Vinciarelli
6,934,166	B2	8/2005	Vinciarelli
6,961,227	B1	11/2005	Whiton et al.
7,027,311	B2	4/2006	Vanderelli et al.
7,235,945	B2	6/2007	Correa et al.
7,400,487	B1	7/2008	Bitar
7,675,197	B2 *	3/2010	Tetlow
2003/0011324	A1	1/2003	Lee
2004/0248742	A1	12/2004	Terashima et al.
2005/0046387	A1	3/2005	Aker et al.
2005/0083059	A1	4/2005	Morita et al.
2005/0148864	A1	7/2005	Slade et al.
2005/0184689	A1	8/2005	Maslov et al.
2006/0098378	A1	5/2006	Gross
2006/0228548	A1	10/2006	Ayai et al.
2007/0018629	A1	1/2007	Potvin et al.
2007/0075053	A1	4/2007	Smith et al.
2007/0145018	A1	6/2007	Smith et al.
2007/0195561	A1	8/2007	Suenaga et al.
2007/0222426	A1	9/2007	Waffenschmidt et al.
2007/0263415	A1	11/2007	Jansen et al.

OTHER PUBLICATIONS

U.S. Appl. No. 12/152,545, filed May 15, 2008, Messer.
U.S. Appl. No. 12/152,525, filed May 15, 2008, Messer.
U.S. Appl. No. 12/313,792, filed Nov. 25, 2008, Issa, et al.
U.S. Appl. No. 12/214,655, filed Jun. 20, 2008, Issa.
U.S. Appl. No. 12/152,977, filed May 15, 2008, Messer.
U.S. Appl. No. 12/152,976, filed May 15, 2008, Messer.
U.S. Appl. No. 60/930,221, filed May 15, 2007, Messer, et al.
U.S. Appl. No. 60/936,506, filed Jun. 20, 2007, Messer, et al.
U.S. Appl. No. 61/004,373, filed Nov. 27, 2007, Messer, et al.
Tracy V. Wilson, How Wireless Power Works, www.howstuffworks.com, Nov. 20, 2008.
Minoru Watanabe, et al. A Study on High Temperature Superconductin Coil of Different Coil Arrangements, IEEE Transactions on Applied Superconductivity, Jun. 2007, vol. 17, No. 2.
Power Requirements for Cooling versus Temperature in Kelvin, www.metox.biz/super_roadmap, Jun. 8, 2008.
Cryostat, Wikipedia Encyclopedia, Jun. 1, 2008.
Resonator, Wikipedia Encyclopedia, Jun. 3, 2008.
Zenergy Receives Order for HTS Induction Heater, Superconductor Week, Oct. 15, 2008, vol. 21 No. 18, Peregrine Communications.
Superconductivity Roadmap, www.metox.biz/super_roadmap, Jun. 8, 2008.

Miyagi, et al., AC Loss Characteristics of an assembled conductor of round Bi2223 Ag sheated wires, Elsevier Science B.V., Aug. 2002, vol. 372-376 Part 3 pp. 1727-1729.

Daumling, et al., Ac loss in superconducting power cables, Studies in High Temperature Superconductors, vol. 33.

O'Miura, et al, The development of a 2.5 T/100 kV A AC superconducting magnet using a high-J NbTi superconducting wire having Nb artificial pins, Supercond. Sci. Techno. Oct. 1993.

HTS-110 Leaders in HTS Magnetic Solutions, www.hts-110.co.nz, Jun. 8, 2008.

Michael Walker, et al., Performance of Coils Wound from Long Lengths of Surface-Coated, Reacted BSCCO-2212 Conductor, IEEE Transactions on Applied Supercond. Jun. 1997, vol. 7 No. 2.

K. Hayashi, et al., Development of Ag-Sheated Bi2223 Superconducting Wires & Thier Applications, IEEE Transactions on Applied Superconductivity, Mar. 2001, vol. 11 No. 1.

A.B. Sneary, et al., Development og High Temperature Superconducting Coils Using Bi-2223/Ag Tapes, IEEE Transactions on Applied Superconductivity vol. 9 No. 2, Jun. 1999.

Mark S. Newson, et al., Progress on the Design and Operation of High-Tc Coils Using Dip-Coat BSCCO-2212/Ag Tape, IEEE Transactions on Applied Superconductivity, vol. 12 No. 1.

L. Bigoni, et al., Development of Bi-2223/Ag Tapes and Coils, IEEE Transactions on Applied Superconductivity, vol. 7 No. 2, Jun. 1997.

Pradeep Halder, et al., Developement of Bi-2223 HTS High Field Coils and Magnets, IEEE Transactions on Applied Superconductivity, Jun. 1995, vol. 5 No. 2.

PJ Masson, et al., HTS Machines as enabling technology for all-electric airborne vehicles, Superconductor Science & Technology, 2007, 748-756.

M. Ariante. et al., Characteristics of Coils wound with Mono and Multifilamentary Bi-2212/Ag from 4 to 80 K, IEEE Transactions on Magnetics vol. 32 No. 4, Jul. 1996.

Shinichi Nomura, et al., Helically Wound Coils for High Field Magnets, IEEE Transactions on Applied Superconductivity, vol. 14 No. 2, Jun. 2004.

Dan Combine, Radiant Energy and Over-Unity, Version 6, Oct. 2006. Tomorrow's High-Temperature Superconducting Cables, www.innovations-report.com, Jun. 27, 2001.

Material Safety Data Sheet for SCS4050, SF12050, SF12100; High Temperature Superconductor Tape, Jun. 12, 2007, SuperPower Inc. International Search Report for PCT/US2008/12013 dated Feb. 4, 2009.

International Search Report for PCT/US2008/06239 dated Aug. 26, 2008.

International Search Report for PCT/US2008/06176 dated Sep. 17, 2008.

International Search Report for PCT/US2008/13097 dated Feb. 4, 2009.

International Search Report for PCT/US2008/07655 dated Sep. 25, 2008.

Wireless Power Tesla Coil Demo, Last Accessed Sep. 14, 2009, <http://www.youtube.com/watch?v=aG-We7A-i9U>.

Miniature Vacuum Tube Tesla Coil, Last Accessed, Nov. 17, 2009, www.capturedlightnin*g.org/hot-streamer/electrontube/minivttc.htm.

MINIVTTC.Bmp Image <http://www.capturedlightning.org/hot-streamer/electrontube/MINIVTTC.bmp>.

NASA SBIR 2009 Phase 1 Form C-Budget Summary.

Information about Principal Investigators/Project directors and co-Principal Investigators/co-Project Directors, Dec. 3, 2009.

Page, Lewis, Lightning-gun tech approaching weaponisation, www.theregister.co.uk, Aug. 26, 2009.

Tobias, John and Grebel H., Self-Imaging in photonic crystals in a subwavelength range, Optice Letters, Dec. 1, 1999, vol. 24, No. 23.

Tobias, John, Ajgaonkar M., Grebel H., Morphology-dependent transmission through photonic crystals, J. Opt. Soc.Am.B., Mar. 2002, vol. 19, No. 3.

Qels 2002, Tuesday Afternoon.

Mar. 15, 2010 Non-final Rejection for U.S. Appl. No. 12/152,976.

Apr. 16, 2010 Notice of Allowance, for U.S. Appl. No. 12/152,977.

Jul. 19, 2010 Notice of Allowance, for U.S. Appl. No. 12/152,977.

Aug. 26, 2010 Notice of Allowance, for U.S. Appl. No. 12/152,977.

Nov. 10, 2010 Ex Parte Quayle Action, for U.S. Appl. No. 12/313,792.

Nov. 5, 2010 Non-final Rejection, for U.S. Appl. No. 12/152,545.

Dec. 8, 2010 Response to Office Action, for U.S. Appl. No. 12/313,792.

Feb. 2, 2011 Notice of Allowance, for U.S. Appl. No. 12/313,792.

* cited by examiner

FIG. 1A




FIG. 1B




FIG. 1C




FIG. 1D




FIG. 1E




FIG. 2





FIG. 3






FIG. 5




FIG. 6




FIG. 7





FIG. 8







FIG. 9B







FIG. 11



METHODS AND SYSTEMS FOR WIRELESS ENERGY AND DATA TRANSMISSION

This application claims the benefit of provisional patent application Ser. No. 61/004,373, filed Nov. 27, 2007. This application hereby incorporates by reference the entire contents of each of U.S. non-provisional patent application Ser. No. 12/152,545 titled "System and Method for Forming and Controlling Electric Arcs," filed May 15, 2008; U.S. non-provisional patent application Ser. No. 12/152,525 titled "System and Method for Controlling an Electromagnetic Field Generator," filed May 15, 2008; and U.S. non-provisional patent application Ser. No. 12/214,655 titled "System and Method for Using a Vacuum Core High Temperature Superconducting Resonator," filed Jun. 20, 2008.

FIELD OF THE INVENTION

The present invention relates to methods and systems for wireless energy and data transmission.

BACKGROUND OF THE INVENTION

It may be desirable to have a system and method for wireless energy and data transmission, especially in fields including, but not limited to, manufacturing, robotics, and consumer devices. By powering devices through wireless transmission of energy, the requirement for batteries or other chemical energy storage means may be reduced. In turn this may reduce the need for copper or aluminum cabling manufacturing costs and battery waste, thereby resulting in more environmentally friendly products.

The use of wireless transmission of energy may also simplify installation, as said devices may be moved without labor intensive rewiring. An additional benefit may be gained from the simultaneous transmission of data over the same carrier wave that transmits the energy for similar reasons of utility, device simplicity, and cost reduction through the use of fewer discrete devices in a given device design. Such use may also conserve bandwidth in other wireless pure data transmission regimes, which may lead to increased network efficiencies.

SUMMARY OF THE INVENTION

In certain aspects, the present invention may provide a system for wirelessly transmitting and receiving energy. In one aspect, the system may include an emitter and a receiver. The emitter may include a primary emitting winding wrapped around a first support and having first and second ends coupled to a driver and a secondary emitting winding wrapped around a second support and having a first end of the secondary emitting winding coupled to a first top load and a second end. The receiver may include a primary receiving winding wrapped around a third support and having first and second ends coupled to first and second inputs of a rectifying circuitry, respectively. The first output of the rectifying circuitry may be coupled to a first terminal of one or more capacitors and a second output of the rectifying circuitry may be coupled a second terminal of the one or more capacitors. The receiver may further include a secondary receiving winding wrapped around a fourth support and having a first end coupled to a second top load and a second end.

In one aspect, the second support may be located within the first support and the fourth support may be located within the third support. In another aspect, the first support may be located with the second support and the third support may be located within the fourth support.

In one aspect, the emitter may include a primary emitting winding wrapped around a first support and having first and second ends coupled to a driver, a secondary emitting winding wrapped around a second support and having first and second ends, and a tertiary emitting winding wrapped around a third support and having a first end of the tertiary emitting winding coupled to the first end of the secondary emitting winding and the second end of the tertiary emitting winding coupled to a first top load. In one aspect, the receiver may include a primary receiving winding wrapped around a fourth support and having first and second ends coupled to first and second inputs of a rectifying circuitry, respectively, where a first output of the rectifying circuitry is coupled to a first terminal of one or more capacitors and a second output of the rectifying circuitry is coupled to a second terminal of the one or more capacitors. The receiver may further include a secondary receiving winding wrapped around a fifth support and having first and second ends and a tertiary receiving winding wrapped around a sixth support and having a first end of the tertiary receiving winding coupled to the first end of the secondary receiving winding and the second end of the tertiary receiving winding coupled to a second top load.

In further aspects, the first support may be located within the second support, the fourth support may be located within the fifth support, the third support may be located above the first and second supports, and the sixth support may be located above the fourth and fifth supports.

In another aspect, the second support may be located with the first support, the fifth support may be located within the fourth support, the third support may be located above the first and second supports, and the sixth support may be located above the fourth and fifth supports.

In one aspect, the present invention may provide for a method of wirelessly transferring data and energy. The method may include inputting a data signal, inputting power to a driver, generating a carrier wave with the driver at a resonant frequency of an emitter, modulating the carrier wave based on the data signal to create a combined signal, driving the combined signal to an AC input on the emitter, electromagnetically coupling the emitter to a receiver, reproducing the combined signal in an AC output of the receiver, rectifying the AC output into DC power, demodulating the combined signal into the data signal, and transmitting the data signal to a device.

In one aspect, the present invention may provide for a method of wirelessly transmitting and receiving energy. The method may include transmitting an alternating current into a driver coupled to a primary emitting winding of an emitter, inducing the alternating current into a secondary emitting winding of the emitter, sensing a frequency of the alternating current on the secondary emitting winding, transmitting a feedback signal to the driver based on the frequency, driving the AC current into the primary emitting winding at the resonant frequency of the secondary emitting winding, electromagnetically coupling the emitter to a receiver, inducing the alternating current into a secondary receiving winding of the receiver, inducing the alternating current into a primary receiving winding of the receiver, outputting the alternating current into a rectifying circuitry, rectifying the alternating current into a direct current; reducing ripples on the direct current, and transmitting the direct current to a device.

BRIEF DESCRIPTION OF THE DRAWINGS

Features and other aspects of embodiments of the present invention are explained in the following description taken in conjunction with the accompanying drawings, wherein:

3

FIG. 1A illustrates a general system including a Tesla coil emitter and receiver according to one aspect of the system and method of the present disclosure;

FIG. 1B illustrates a general system including a Tesla coil emitter and receiver in plan view according to one aspect of the system and method of the present disclosure;

FIG. 1C illustrates a schematic representation of a Tesla coil emitter and receiver according to one aspect of the system and method of the present disclosure;

FIG. 1D illustrates a general system including Tesla coil emitter and receiver each with tertiary windings and the primary windings located within the secondary windings according to one aspect of the system and method of the present disclosure;

FIG. 1E illustrates a receiver including materials of high magnetic permeability according to one aspect of the system and method of the present disclosure;

FIG. 2 illustrates a driving circuit detail according to one aspect of the system and method of the present disclosure;

FIG. 3 illustrates a magnetic field coupling of the coils according to one aspect of the system and method of the present disclosure;

FIG. 4 illustrates a receiver rectification circuit detail with capacitor bank according to one aspect of the system and method of the present disclosure;

FIG. 5 illustrates a variable tap implemented on Tesla coil according to one aspect of the system and method of the present disclosure;

FIG. 6 illustrates an example of application of a system to provide power for utilization according to one aspect of the system and method of the present disclosure;

FIG. 7 illustrates a coaxial orientation of emitter and receiver according to one aspect of the system and method of the present disclosure;

FIG. 8 illustrates a Tesla coil emitter and receiver according to one aspect of the system and method of the present disclosure;

FIG. 9A illustrates a reversible Tesla coil system where the function of emitter and receiver may alternate according to one aspect of the system and method of the present disclosure;

FIG. 9B illustrates circuitry for a reversible Tesla coil system where the function of emitter and receiver may alternate according to one aspect of the system and method of the present disclosure;

FIG. 10 illustrates a representative example of a network of Tesla coil emitters and receivers according to one aspect of the system and method of the present disclosure;

FIG. 11 illustrates a representative method of information and power transmission using a Tesla coil system according to one aspect of the system and method of the present disclosure;

The drawings are exemplary, not limiting. It is intended for items that are labeled with the same number in multiple figures to refer to the same item throughout the figures.

DETAILED DESCRIPTION

Various embodiments of the present invention will now be described in greater detail with reference to the drawings.

As shown in FIG. 1A, one aspect may include two Tesla resonators **101** and **102**, which may be electromagnetically coupled through emitting a time-varying magnetic and/or electric field **9**. Tesla resonators **101** and **102** may be oriented parallel to each other. The emitting Tesla resonator apparatus ("emitter") **101** may emit the field, while the receiving Tesla coil apparatus ("receiver") **102** may subtend the magnetic field from the emitter **101**. Parallel orientation of emitter **101**

4

and receiver **102** may ensure maximum flux coupling between them. Emitter **101** may include primary winding **1E**, secondary winding **2E**, support apparatus for primary winding **10E**, and support apparatus for secondary winding **20E**; receiver **102** may include primary winding **1R**, secondary winding **2R**, support apparatus for primary winding **10R**, and support apparatus for secondary winding **20R**. Primary and secondary windings **1E**, **1R**, **2E**, and **2R** may be composed of any common wiring material used in the implementation or construction of coils and transformers. Other aspects may use other materials. Primary structural supports **10E** and **10R** and secondary structural supports **20E** and **20R** may be composed of ceramic, plastic, Plexiglas, RTM., or any other insulating or nonconductive (e.g., dielectric) material. Primary winding **1E** and **1R** may be wrapped around primary structural supports **10E** and **10R**, respectively, and secondary windings **2E** and **2R** may be wrapped around secondary structural supports **20E** and **20R**, respectively. Windings **1E**, **1R**, **2E**, and **2R** may be wrapped in a helically-coiled fashion, where each primary winding **1E** and **1R** is oriented similarly as its respective secondary winding **2E** and **2R**. In such aspects, the ends of each winding may not be helically-coiled, as, in various aspects, they may be coupled to other windings, circuitry, or to ground. Primary and secondary structural supports **10E**, **10R**, **20E**, and **20R** may be cylindrical in shape. With respect to structural supports and windings, emitter **101** may be substantially identical to, or identically arranged as, receiver **102**.

In one aspect, primary windings **1E** and **1R** may be 6 AWG wire; secondary windings **2E** and **2R** may be 24 AWG wire; and tertiary windings **3E** and **3R** may be 28 AWG wire. In another aspect, secondary windings **2E** and **2R** may have 1,800 turns; tertiary windings **3E** and **3R** may have 2,400 turns; primary receiver winding **1R** may have 12 turns; and primary emitter winding **1E** may have 28 turns. In other aspects, other wire and different number of turns may be used. The drawings of the windings in the figures are not intended to show the exact number of turns or ratio of turns used in aspects of the present invention. In one aspect, primary structural supports **10E** and **10R** may be about 12 inches each in diameter; secondary structural supports **20E** and **20R** may be about 8 inches each in diameter; and tertiary structural supports **40E** and **40R** may be each about 6 inches in diameter. In one aspect, top loads **30E** and **30R** may be each about 2.5 inches thick, about 8 inches in outer diameter, and about 6 inches in inner diameter. In one aspect having primary windings **1E** and **1R** located within secondary windings **2E** and **2R**, respectively (as shown in FIG. 1D according to one aspect), primary structural supports **10E** and **10R** may have a smaller diameter than secondary structural supports **20E** and **20R**, for example, 6 inches in outer diameter. In one aspect having tertiary windings **3E** and **3R**, an end cap made of a nonconductive material may be used on the larger of the primary and secondary structural supports **10E**, **10R**, **20E**, and **20R** in order to provide a base for tertiary structural supports **40E** and **40R**. In other aspects, other sized supports and top loads may be used.

In one aspect, top load **30E** and/or **30R** may be provided on the secondary winding **2E** and/or **2R** that may reduce eddy currents and corona and thereby may reduce electric leakage of the device through corona. Secondary top load **30E** and **30R** may be comprised of a toroidal metal shape with a hole cut out of the center of the toroid that is penetrated by the inner diameter of secondary support **20E** and/or **20R** of secondary winding **2E** and/or **2R**. In these aspects, the final coil in the series (whether secondary or tertiary) may receive top load **30E** and/or **30R**. Using top load **30E** and/or **30R** may reduce energy loss by about 5-10% by reducing eddy currents. In

5

another aspect, toroidal top load **30E** and/or **30R** may also use a vertical slit as opposed to the circular hole for similar purposes and effects.

As shown in FIG. 1D, one aspect may include primary windings **1E** and **1R** wrapped around primary structural supports **10E** and **10R**, respectively, and have primary structural supports **10E** and **10R** located within secondary structural supports **20E** and **20R**, respectively. In further aspects, one or more tertiary windings **3E** and **3R** may be wrapped around tertiary structural supports **40E** and **40R**, respectively, which sit on top of primary and secondary structural supports **10E**, **20E**, **10R**, and **20R**. In further aspects, tertiary emitting winding **3E** having two ends wrapped around tertiary support structure **40E** may be coupled to the end of secondary emitting winding **2E** that is not connected to ground. The other end of the tertiary emitting winding **3E** may be connected to top load **30E** (or, in other aspects, to another emitting winding in the same pattern (not shown)). In further aspects, tertiary emitting winding **3E** may have more windings than secondary emitting winding **2R** in order to create more voltage if more voltage is desired.

In further aspects, tertiary receiving winding **3R** having two ends wrapped around tertiary support structure **40R** may be connected to the end of secondary receiving winding **2R** that is not connected to ground. The other end of tertiary receiving winding **3R** may be connected to top load **30R** (or, in other aspects, to another emitting winding in the same pattern (not shown)). In further aspects, tertiary receiving winding **3R** may have more windings than secondary receiving winding **2R** in order to create more voltage if more voltage is desired.

In further aspects, the system may include one or more tertiary Tesla resonators (not shown) or emitters (not shown). In further aspects, additional windings may be used; therefore, aspects are not intended to be limited to merely two or three windings.

In further aspects, AC voltage **4** may be presented through application of a solid state driving system that drives primary emitting winding **1E** at the resonant frequency of Tesla resonators' **101** and **102**. Receiver **102** may receive energy through electromagnetic coupling to emitter **101**.

In further aspects, the coil structure of emitter **101** and receiver **102** may be substantially identical, with one difference being the driving circuitry of emitter **101** and the rectification circuitry of receiver **102**. In further aspects, emitter **101** and receiver **102** may be provided with the rectification and switching circuits along with circuitry to switch between the two, so that energy may be transferred back and forth between emitter **101** and receiver **102**. In further aspects, an electromagnetic field couples emitter **101** to receiver **102**. Current from primary winding emitter **1E** ultimately may couple through the exchange of electromagnetic energy into receiver **102**. That is, primary emitting winding **1E** may induce AC voltage **99** on primary receiving winding **1R** through electromagnetic coupling between emitter **101** and receiver **102**. AC out **99** may be rectified by full bridge rectifier **5** and may charge capacitor **6** with DC out **91** voltage.

In aspects, emitter **101** and receiver **102** may be spatially distributed, either in fixed positions or mobile. These fixed positions may not be in set locations, so long as receiver **102** is within a certain range of emitter **101** that may be determined by the electromagnetic field intensity of a particular device. Likewise, a mobile receiver **102** may not be required to be constrained to a track or fixed path but so long as it remains within a certain range of one or more emitters **101**. In further aspects, multiple emitters **101** and receivers **102** may be used, where several receivers **102** may draw energy from

6

one emitter **101** or a single receiver **102** may draw energy from multiple emitters **101** (and so forth).

FIG. 1B displays emitter **101** and receiver **102** in plan view according to one aspect of the system of the present disclosure.

FIG. 1C shows an electrical schematic according to one aspect. The resonant frequency is given by equation $f_r = 1/(2\pi \sqrt{LC})$, where C is capacitive value of **13R** and L is inductive value of lumped inductance **12R** of secondary emitting winding **2E**.

As shown in FIG. 1C, further aspects may include secondary emitting winding **2E** and loading capacitor **13R**, which may be attached to ground **8E** and **8R**. In further aspects, secondary emitting winding **2E** may be floating, that is, not connected to electrical ground. In further aspects, loading capacitor **13R** may be floating.

As shown in FIG. 1E, one aspect may include cylinders of high permeability material (e.g., iron, Mu metal, HyMu80) **50R** and **60R** in structural supports **30R** and **40R**, respectively. Use of cylinders of high permeability material **50R** and **60R** in receiver **102** may make the power transfer more efficient between emitter **101** and receiver **102** by concentrating the magnetic flux within the windings surrounding the cylinders of high permeability material **50R** and **60R**. In one aspect, cylinders of high permeability material **50R** and **60R** may be solid. In another aspect, cylinders of high permeability material **50R** and **60R** may be hollow, such as, a sheet of such material wrapped into a cylindrical form. In other aspects, high permeability material **50R** and **60R** may be a form in shapes other than a cylinder.

FIG. 2 shows the driving circuit of emitter **101** according to one aspect of the system of the present disclosure. Primary emitting winding **1E** may be driven by insulated gate bipolar transistors ("IGBT"s) **16**, **17**, **18**, and **19** in an H-bridge configuration with a power source **3**. The AC signal to primary emitting winding **1E** may thereby induce a voltage in secondary winding **2E**, initiating the Tesla coil effect.

Further aspects may include a feedback system that monitors the direction of current via current drive transformer **14**. In one aspect, current drive transformer **14** is coupled to secondary emitting winding **20E**. Current drive transformer **14** may sense current on secondary emitting winding **20E**, where current drive transformer **14** may provide voltage in response to oscillation at the resonant frequency of secondary emitting winding **20E**. Digital feedback signal **15** may be a logic "1" signifying current flowing in one direction and a logic "0" signifying current flowing in the opposite direction. Feedback signal **15** may allow the H-bridge to determine when to switch its transistors such that induced current flows into emitter **101** from primary emitting winding **1E** may constructively interfere to increase magnetic flux in emitter **101**. In further aspects, the feedback system drives primary emitting winding **1E** at the resonant frequency of secondary emitting winding **2E**.

In further aspects, feedback signal **15**, filtered with inverting **131** and non-inverting **13B** IGBT gate drive system, may create logic signals **20a** and **20b**. Logic signals **20a** and **20b** may drive the H-bridge with the frequency, phase, and polarity for an AC in wave to flow to primary emitter winding **1E** to amplify the resonating field in emitter **101**. Thus, the device may be self-correcting in phase and frequency.

FIG. 3 shows a magnetic field coupling between emitter **101** and receiver **102** according to one aspect. Magnetic flux lines **22** are intended to be drawn to show that secondary receiving winding **2R** of receiver **102** is immersed in field **22**. In further aspects, AC voltage **99** may result from the magnetic field coupling and the effect of secondary receiving

7

winding 2R and primary receiving winding 1R. Because of the physical properties of Tesla coils, when an exciting voltage is presented to 99, receiver 102 may be capable of acting as an emitter and transferring energy to emitter 101.

Wireless energy transfer may allow the conversion of the AC signal 99 from primary receiving winding 1R into a useful form. As shown in FIG. 4, according to one aspect of the system of the present disclosure, the conversion of AC voltage output 99 to DC voltage across capacitor 27 may occur from induced current in primary receiver winding 1R, which was demonstrated as induced by a coupled magnetic field between Tesla resonators 101 and 102. DC voltage exiting diode array 24 may be imperfect because of possible ripples. Output current 99 may be rectified via high recovery speed diodes and diode array 24 and stored into, for example, capacitor bank 401, as shown according to one aspect. In further aspects, high recovery speed diodes and diode array 24 may be rated at, for example, 1200V, 60 A with a reverse recovery time of 30 ns and a speed for fast recovery ≤ 500 ns and ≥ 200 mA. In one aspect, adding diodes (not shown) to diode array 24 may allow the system to handle higher voltages.

In further aspects, capacitor bank 401 may be a system of capacitors for the purpose of storing energy. The system may include low inductance polymeric capacitor 26 and snubber capacitor 25 acting as filters connected in parallel to electrolytic capacitor 27 acting as a storage capacitor for fast charging and discharging of capacitors 25, 26, and 27. Low internal and external stray inductance may be achieved by minimum length of wires interconnecting capacitors 25 and 26 and capacitor 27. Diode array 24 may be connected to inputs of capacitor bank 401 through leads 402 and 403 between the positive (+) and negative (-) outputs on diode array 24 and the positive (+) and negative (-) inputs on capacitor bank 401. In further aspects, minimizing and equalizing the inductance of leads 402 and 403 may be accomplished by ensuring leads 402 and 403 are of equal length, and as short as possible.

As shown in FIG. 5, further aspects may include variable tap 28 on primary receiving winding 1R of receiver 102. Variable tap 28 may be a moveable and changeable connection on a transformer through which the voltage may be changed. Variable tap 28 may change the voltage output to the voltage input ratio, similar to the ways an iron core transformer with multiple primary taps may change in voltage with relative voltage output to voltage input ratio change. Because in aspects, the system is reversible, variable tap 28 may be coupled to primary emitting winding 1E or emitter 101.

As shown in FIG. 6, further aspects may include receiver 102 with primary receiver winding 1R and variable pick-up tap 28. For example, if it is desired to have 12 VDC for a standard DC-to-AC (60 Hz) inverter, primary receiver winding 1R may be tapped by variable tap 28, such that the RF output may be about ~ 10 Vrms, which yields about ~ 14 Vdc, so up to about 2 Vdc may be lost by forward diode drops over rectifying diodes 24. DC rectifying array 24 and capacitors 25, 26, and 27 may allow stable and constant DC power to inverter 31. In further aspects, this may be a particularly useful configuration due to the widespread use of 60 Hz 120 VAC for power applications. However, many different DC and AC outputs could be synthesized from the signal generated by primary receiving winding 1R. In one aspect, device 602 may receive DC power from the system by being connected to positive (+) output 27 through wire 601, and device 32 may receive AC power from DC inverter 31.

As shown in FIG. 7 according to aspects, emitter 101 and receiver 102 may be oriented in a manner whereby the windings could remain parallel but share a common coil axis. Alternatively, in further aspects, the coils may be oriented in

8

a similar configuration, for example, as shown in FIG. 1A, but without a common coil axis (not shown), for example, if two coils were placed on different floors of a building (like at the top-left corner of a second floor and bottom right corner of a first floor). In other aspects, emitter 101 and receiver 102 may be transposed such that top loads 30E and 30R are facing each other.

As shown in FIG. 8 according to further aspects, because it is possible to achieve high voltages on secondary windings 2E and 2R, an arc suppression system may be implemented on emitter 101. FIG. 8 is illustrated to show such an aspect, given the cylinders labeled 38 surrounding windings 1R, 2R, 1E, and 2E are constructed as, for example, a gas tight enclosure. In another aspect, emitter 101 and/or receiver 102 may be immersed in an atmosphere of higher dielectric breakdown strength compared to air (for example, sulfur hexafluoride) to suppress corona and breakdown arcs. In one aspect, cylinders 38 may be vacuums.

In one aspect, emitter 101 and receiver 102 may be screened by a Faraday-cage type of enclosure 801 to reduce electric fields around the system. This aspect may operate as a transformer. Driving circuitry 4 may be inside or outside Faraday-cage type of enclosure 801, but the power supply to driving circuitry 4 is outside Faraday-cage type of enclosure 801. Wire 601 may transfer DC power to device 602 outside Faraday-cage type of enclosure 801. In one aspect, Faraday-cage type of enclosure 801 is connected to ground 7. In one aspect, secondary windings 2E and 2R are floating and, therefore, are not connected to grounds 8E and 8R.

As shown in FIGS. 9A and 9B, according to one aspect of the present disclosure, Tesla resonators 1501 and 1502 may couple energy to each other and may be "reversible," i.e., each Tesla resonator 1501 and 1502 may emit and receive energy so either one may be used. In FIG. 9A, resonators 1501 and 1502 are each coupled to driving circuits 901 and 902 so each may act as an emitter and/or a receiver. In one aspect, if IGBT 35 of circuit 901 is set to closed by logic signal 200, then circuit 901 would function as downstream circuitry of receiver 102 and, therefore, would ultimately produce DC current at DC out 36 (as shown in FIG. 6). In one aspect, if IGBT 35 of circuit 901 is set to open by logic signal 20Q, then circuit 901 would function as emitter 101.

As shown in FIG. 10, in one aspect, the system of the present disclosure may include receivers 1003R, 1005R, and 1006R and emitters 1001E, 1002E, and 1004E may be arranged to relay energy. In one aspect, two emitters 1001 and 1002 transmit energy wirelessly to a receiver 1003R that is connected through, for example, wires 1008 and 1009 to a third emitter 1004E. Emitter 1004E may then wirelessly power three separate receivers 1005R, 1006R, and 1007R. It should be noted that this illustration is provided as an example of a repeater winding network and not as a limiting design.

As shown in FIG. 11, another aspect of the system of the present disclosure may include the use of imposing a modulation upon the basic carrier wave emitted from emitter 101. Any number of digital or analog modulation methods or schemes may be applied to a basic carrier wave. After reception by receiver 102, the carrier wave may be demodulated to provide information transfer while using the same carrier wave for power transfer. This simultaneous transfer of information and power may be effectuated by using the same devices discussed in aspects of the present invention, e.g., emitter 101 and receiver 102.

For example, in one aspect, the system may transmit energy along with an audio signal. The audio signal may be modulated, such as with pulse width modulation (PWM) or amplitude modulation (AM) onto, for example, an 80 kHz

power carrier signal from emitter **101E** to receiver **102R** embodied within a speaker assembly. One of ordinary skill in the art would understand that alternative modulation schemes, such as, frequency modulation (FM) or phase modulation, may be used with the system as described in aspects of the present disclosure.

In one aspect, signal input **1702** is modulated using modulator **1703** and combined with power input **1701** through the driving circuit **4Q** (as shown according in FIG. 2 according to one aspect of the present invention). In this aspect, the high-frequency side of the input signal becomes a mixer, imposing the data signal on AC input **99**, which is the carrier wave frequency, generated by driving circuit **4Q**. The speaker assembly with emitter **101E** may be placed anywhere within a range of receiver **102R** and be self-powered by reception of power from emitter **101E** to drive electronics to demodulate the carrier signal to reproduce the audio signal.

In further aspects, demodulator **1704** may be placed to sense combined signal **99** reproduced at the output of the receiver **102R**. The signal may be sensed by direct connection or by other means familiar to one of ordinary skill in the art. Data signal **1706** is then produced by demodulator **1704**. The carrier component of signal **99** is fed into circuitry **1705**, which may include diode array **24** (as shown in FIG. 4 according to one aspect), capacitor bank **401** (as shown in FIG. 4 according to one aspect), and circuitry **603** (as shown in FIG. 6 according to one aspect) as necessary to produce power.

In one aspect, circuitry for performing driving circuitry **4Q** and modulator **1703** are described in U.S. non-provisional patent application Ser. No. 12/152,525 titled "System and Method for Controlling an Electromagnetic Field Generator," filed May 15, 2008.

Although illustrative embodiments have been shown and described herein in detail, it should be noted and will be appreciated by those skilled in the art that there may be numerous variations and other embodiments that may be equivalent to those explicitly shown and described. For example, the scope of the present invention is not necessarily limited in all cases to execution of the aforementioned steps in the order discussed. Unless otherwise specifically stated, terms and expressions have been used herein as terms of description, not of limitation. Accordingly, the invention is not to be limited by the specific illustrated and described embodiments (or the terms or expressions used to describe them) but only by the scope of claims.

The invention claimed is:

1. A system for wirelessly transmitting and receiving energy, comprising:

an emitter, comprising:

a primary emitting winding wrapped around a first support and having first and second ends coupled to a driver; and

a secondary emitting winding wrapped around a second support and having a first end of the secondary emitting winding coupled to a first top load and a second end; and

a receiver, comprising:

a primary receiving winding wrapped around a third support and having first and second ends coupled to first and second inputs of a rectifying circuitry, respectively, where a first output of the rectifying circuitry is coupled to a first terminal of one or more capacitors and a second output of the rectifying circuitry is coupled to a second terminal of the one or more capacitors; and

a secondary receiving winding wrapped around a fourth support and having a first end coupled to a second top load and a second end;

wherein the second support is located within the first support and the fourth support is located within the third support.

2. The system of claim 1, wherein the second support is approximately concentric with the first support and the fourth support is approximately concentric with the third support.

3. The system of claim 1, further comprising a Faraday cage containing the emitter and the receiver.

4. The system of claim 1, wherein the rectifying circuitry includes a diode array.

5. The system of claim 1, wherein the one or more capacitors includes one or more snubber capacitors, low inductance polymeric capacitors, and electrolytic capacitors.

6. The system of claim 1, wherein a device is coupled to a positive output of the one or more capacitors.

7. The system of claim 1, wherein the driver includes a feedback system and insulated gate bipolar transistors in an H-bridge configuration.

8. The system of claim 1, further comprising a variable tap coupled to the primary receiving winding.

9. The system of claim 1, further comprising a first gas-tight container surrounding the emitter and a second gas-tight container surrounding the receiver.

10. The system of claim 9, wherein the first and second gas-tight containers include a gas with a high-dielectric atmosphere.

11. The system of claim 9, wherein the first and second gas-tight containers are vacuums.

12. The system of claim 1, wherein the first, second, third, and fourth supports are non-conductive tubes.

13. The system of claim 1, wherein the second end of the secondary emitting winding is coupled to a first ground.

14. The system of claim 1, wherein the second end of the secondary receiving winding is coupled to a first ground.

15. The system of claim 13, wherein the second end of the secondary receiving winding is coupled to a second ground.

16. The system of claim 1, wherein the one or more capacitors comprises a capacitor bank.

17. A system for wirelessly transmitting and receiving energy, comprising:

an emitter, comprising:

a primary emitting winding wrapped around a first support and having first and second ends coupled to a driver;

a secondary emitting winding wrapped around a second support and having first and second ends; and

a tertiary emitting winding wrapped around a third support and having a first end of the tertiary emitting winding coupled to the first end of the secondary emitting winding and the second end of the tertiary emitting winding coupled to a first top load; and

a receiver, comprising:

a primary receiving winding wrapped around a fourth support and having first and second ends coupled to first and second inputs of a rectifying circuitry, respectively, where a first output of the rectifying circuitry is coupled to a first terminal of one or more capacitors and a second output of the rectifying circuitry is coupled to a second terminal of the one or more capacitors;

a secondary receiving winding wrapped around a fifth support and having first and second ends; and

a tertiary receiving winding wrapped around a sixth support and having a first end of the tertiary receiving

11

winding coupled to the first end of the secondary receiving winding and the second end of the tertiary receiving winding coupled to a second top load; wherein the first support is located within the second support, the fourth support is located within the fifth support, the third support is located above the first and second supports, and the sixth support is located above the fourth and fifth supports.

18. The system of claim 17, wherein the second end of the secondary emitting winding is coupled to a first ground.

19. The system of claim 17, wherein the second end of the secondary receiving winding is coupled to a first ground.

20. The system of claim 18, wherein the second end of the secondary emitting winding is coupled to a first ground.

21. A method of wirelessly transferring data and energy, comprising:

- (a) inputting a data signal;
- (b) inputting power to a driver;
- (c) generating a carrier wave with the driver at a resonant frequency of an emitter;
- (d) modulating the carrier wave based on the data signal to create a combined signal;
- (e) driving the combined signal to an AC input on the emitter;
- (f) electromagnetically coupling the emitter to a receiver;
- (g) reproducing the combined signal in an AC output of the receiver;
- (h) rectifying the AC output into DC power;
- (i) demodulating the combined signal into the data signal; and
- (j) transmitting the data signal to a device.

22. The method of claim 21, wherein the data signal is an audio signal.

23. The method claim 21, wherein the data signal is modulated using one of amplitude modulation, pulse width modulation, frequency modulation, and phase modulation.

24. The method of claim 21, wherein the device is an audio speaker.

25. The method of claim 21, wherein the rectifying the AC output into DC power is done through a rectifying circuitry and a capacitor bank.

26. The method claim 21, wherein the driver includes a feedback system and insulated gate bipolar transistors in an H-bridge configuration.

27. The method of claim 21, wherein the modulating step further comprises modulating the amplitude of the carrier wave.

28. The method of claim 21, wherein, the emitter comprises:

- a primary emitting winding wrapped around a first support and having first and second ends coupled to a driver;
- a secondary emitting winding wrapped around a second support and having first and second ends; and
- a tertiary emitting winding wrapped around a third support and having a first end of the tertiary emitting winding coupled to the first end of the secondary emitting winding and the second end of the tertiary emitting winding coupled to a first top load; and

the receiver comprises:

- a primary receiving winding wrapped around a fourth support and having first and second ends coupled to first and second inputs of a rectifying circuitry, respectively, where a first output of the rectifying circuitry is coupled to a first terminal of one or more

12

capacitors and a second output of the rectifying circuitry is coupled to a second terminal of the one or more capacitors;

a secondary receiving winding wrapped around a fifth support and having first and second ends; and

a tertiary receiving winding wrapped around a sixth support and having a first end of the tertiary receiving winding coupled to the first end of the secondary receiving winding and the second end of the tertiary receiving winding coupled to a second top load.

29. The method of claim 21, wherein the emitter comprises:

- a primary emitting winding wrapped around a first support and having first and second ends coupled to a driver;
- a secondary emitting winding wrapped around a second support and having a first end of the secondary emitting winding coupled to a first top load and a second end; and

the receiver comprises:

- a primary receiving winding wrapped around a third support and having first and second ends coupled to first and second inputs of a rectifying circuitry, respectively, where a first output of the rectifying circuitry is coupled to a first terminal of one or more capacitors and a second output of the rectifying circuitry is coupled to a second terminal of the one or more capacitors; and
- a secondary receiving winding wrapped around a fourth support and having a first end coupled to a second top load and a second end.

30. A system for wirelessly transmitting and receiving energy, comprising:

an emitter, comprising:

- a primary emitting winding wrapped around a first support and having first and second ends coupled to a first driver, wherein the first driver is coupled to first and second inputs of a rectifying circuitry respectively, where a first output of the rectifying circuitry is coupled to one or more capacitors through a first terminal of the one or more capacitors and a second output of the rectifying circuitry is connected to the one or more capacitors through a second terminal of the one or more capacitors; and
- a secondary emitting winding wrapped around a second support and having a first end of the secondary emitting winding coupled to a first top load and a second end; and

a receiver, comprising:

- a primary receiving winding wrapped around a third support and having first and second ends coupled to a second driver, wherein the second driver is coupled to first and second inputs of a rectifying circuitry respectively, where a first output of the rectifying circuitry is coupled to one or more capacitors through a first terminal of the one or more capacitors and a second output of the rectifying circuitry is connected to the one or more capacitors through a second terminal of the one or more capacitors; and
- a secondary receiving winding wrapped around a fourth support and having a first end coupled to a second top load and a second end;

wherein the first support is located within the second support and the third support is located within the fourth support.

13

31. A method for wirelessly transmitting and receiving energy, comprising:

- (a) transmitting an alternating current into a driver coupled to a primary emitting winding of an emitter;
- (b) inducing the alternating current into a secondary emitting winding of the emitter;
- (c) sensing a frequency of the alternating current on the secondary emitting winding;
- (d) transmitting a feedback signal to the driver based on the frequency;
- (e) driving the AC current into the primary emitting winding at the resonant frequency of the secondary emitting winding;
- (f) electromagnetically coupling the emitter to a receiver;
- (g) inducing the alternating current into a secondary receiving winding of the receiver;
- (h) inducing the alternating current into a primary receiving winding of the receiver;
- (i) outputting the alternating current into a rectifying circuitry;
- (j) rectifying the alternating current into a direct current;
- (k) reducing ripples on the direct current; and
- (l) transmitting the direct current to a device.

32. A system for wirelessly transmitting and receiving energy, comprising:

a reversible emitter, comprising:

- a primary emitting winding wrapped around a first support and having first and second ends coupled to a first driver, wherein the first driver is coupled to a first rectifying circuitry, wherein the first rectifying circuitry is coupled to a first one or more capacitors;
- a secondary emitting winding wrapped around a second support and having first and second ends; and
- a tertiary emitting winding wrapped around a third support and having a first end of the tertiary emitting winding coupled to the first end of the secondary emitting winding and the second end of the tertiary emitting winding coupled to a first top load; and

a reversible receiver, comprising:

- a primary receiving winding wrapped around a fourth support and having first and second ends coupled to a second driver, wherein the second driver is coupled to

14

a second rectifying circuitry, wherein the second rectifying circuitry is coupled to a second one or more capacitors;

- a secondary receiving winding wrapped around a fifth support and having first and second ends; and
 - a tertiary receiving winding wrapped around a sixth support and having a first end of the tertiary receiving winding coupled to the first end of the secondary receiving winding and the second end of the tertiary receiving winding coupled to a second top load;
- wherein the second support is located within the first support, the fifth support is located within the fourth support, the third support is located above the first and second supports, and the sixth support is located above the fourth and fifth supports.

33. The system of claim 32, wherein

the first driver comprises:

- insulated gate bipolar transistors in an H-bridge configuration; and
- a switch for activating the first rectifying circuitry and the first one or more capacitors; and

the second driver comprises:

- insulated gate bipolar transistors in an H-bridge configuration; and
- a switch for activating the second rectifying circuitry and the second one or more capacitors.

34. The system of claim 1, wherein the fourth support surrounds a form including a high permeability material.

35. The system of claim 17, wherein the fifth and sixth supports each surround forms including a high permeability material.

36. The method of claim 28, wherein the fifth and sixth supports each surround forms including a high permeability material.

37. The system of claim 29, wherein the fourth support surrounds a form including a high permeability material.

38. The system of claim 30, wherein the fourth support surrounds a form including a high permeability material.

39. The system of claim 32, wherein the fifth and sixth supports each surround forms including a high permeability material.

* * * * *